## Inertial Sensor Arrays – A Literature Review

John-Olof Nilsson and Isaac Skog

Dept. Signal Processing, KTH Royal Institute of Technology, Stockholm, Sweden

Abstract—Inertial sensor arrays present the possibility of improved and extended sensing capabilities as compared to customary inertial sensor setups. Inertial sensor arrays have been studied since the 1960s and have recently received a renewed interest, mainly thanks to the ubiquitous micro-electromechanical (MEMS) inertial sensors. However, the number of variants and features of inertial sensor arrays and their disparate applications makes the literature spread out. Therefore, in this paper we provide a brief summary and literature review on the topic of inertial sensor arrays. Publications are categorized and presented in a structured way; references to +300 publications are provide. Finally, an outlook on the main research challenges and opportunities related to inertial sensor arrays is given.

#### I. INTRODUCTION

An inertial sensor arrays is the concept of combining redundant accelerometer and gyroscope sensing elements. The interest in such arrays comes from their ability to provide properties and capabilities not attainable from conventional, non-redundant sensor assemblies, i.e. inertial measurement units (IMUs) made out of three accelerometers and three gyroscopes. In short, the attainable capabilities are:

- Higher accuracy
- Higher reliability and uncertainties estimation
- Higher dynamic measurement range
- Estimation of angular motion from accelerometer data
- Direct estimation of angular acceleration

Owing to these desirable properties and capabilities, inertial sensor arrays have been an active research topic since the 1960s and the research literature consists of some +300 publications and +10 PhD theses; publications that are covering different aspects related to the design and development of inertial sensor arrays, such as measurement fusion, calibration and geometry optimization. The application areas range from inertial navigation for aerospace to vehicle crash test systems. The disparate topics of the publications and varying application areas mean that the publications are dispersed out over a wide range of research fields and many results are reproduced over and over again. The aim of this paper is therefore to provide a brief review of the literature and summarize the key findings. It is the authors' hope that this will provide the interested reader with an overview of the topic and inspire further research in an area where the rapid development of sensor and computational technologies provides many new opportunities.

Fault detection and identification is an important capability of inertial sensor arrays, but rather separated from the other capabilities. Therefore, we have chosen to omit it from this literature review. The interested reader is referred to [26], [317], [134] and the references therein. The review has further



Fig. 1. An illustration of the forces sensed by the accelerometers in an inertial sensor array, overlaid on a picture of an inertial sensor array constructed from 32 IMUs [270]. The specific force sensed by the *i*:th accelerometer triad is the sum of the specific force at the origin of the array coordinate frame, the centrifugal force, and the Euler force.

been limited to English literature. The references are numbered in alphabetical order.

#### II. INERTIAL SENSOR ARRAYS

The properties and capabilities of an inertial array are best understood with a basic array signal model. For simplicity, assume an array consisting of  $N_s$  accelerometer and  $N_{\omega}$ gyroscope triads. Further, assume that the sensors are identical, their sensitivity axes aligned, and that they have an additive measurement error. The measurements of the *i*:th accelerometer triad and *j*:th gyroscope triad can then be modelled as

$$\mathbf{y}_{s}^{(i)} = \mathbf{s} + \underbrace{\boldsymbol{\omega} \times (\boldsymbol{\omega} \times \mathbf{r}^{(i)})}_{\text{Centrifugal force}} + \underbrace{\dot{\boldsymbol{\omega}} \times \mathbf{r}^{(i)}}_{\text{Euler force}} + \mathbf{n}_{s}^{(i)} \qquad (1)$$

and

$$\mathbf{y}_{\omega}^{(j)} = \boldsymbol{\omega} + \mathbf{n}_{\omega}^{(j)} \tag{2}$$

respectively. Here s is the specific force at the origin of the array coordinate system and  $\mathbf{r}^{(i)}$  is the location of the *i*:th accelerometer triad.  $\omega$  and  $\dot{\omega}$  are the array's angular velocity and angular acceleration, respectively.  $\mathbf{n}_{s}^{(i)}$  and  $\mathbf{n}_{\omega}^{(j)}$ are the measurement errors of the accelerometer triads and gyroscope triads, respectively. See Fig. 1. for an illustration of the accelerometer measurement components and the geometry. From the measurement models it can be observed that: (i) the accelerometers provide information both about the linear motion and the rotational motion (angular velocity and angular acceleration), whereas the gyroscopes only provide rotation information; (ii) the rotation information gained from the accelerometers depends on the geometry and scale of the array; and (iii) there is a sign ambiguity in the angular velocity information provided by the accelerometers, i.e.,  $\omega \times \omega =$  $(-\boldsymbol{\omega}) \times (-\boldsymbol{\omega}).$ 

### A. Capabilities

From the listed observations it follows that with an array of inertial sensors the following capabilities can be obtained<sup>1</sup>:

• *Higher accuracy*: By simply averaging the accelerometer and gyroscope measurements the specific force and angular velocity error covariance can be reduced by a factor  $N_s$  and  $N_{\omega}$ , respectively<sup>2</sup>. However, since the accelerometers also provide rotational information, the angular velocity estimation accuracy can be improved further by fusing the information from both the accelerometers and gyroscopes. The additional information<sup>3</sup> (accuracy) gained is proportional to the square of the angular speed. Refer to [273] for details about the information gain and a lower bound for the estimation accuracy. Further, with asynchronous sensors an effective higher sampling rate than that of individual sensors can be achieved [270].

• Extended sensing: The possibility of extracting rotational information from the accelerometers implies that it is possible to construct an array of only accelerometers and still be able to estimate both the linear and the rotational motions. Further, in the case of an array consisting of both accelerometers and gyroscopes, this possibility also implies that the angular velocity can be estimated, even though the gyroscopes are saturated, i.e., the angular velocity dynamic range is increased [273]. Moreover, since the accelerometers also provide information regarding the angular acceleration, this can be directly estimated, and the noise amplifying differentiation of gyroscope measurements avoided [258]. Finally, in principle (though not seen from the basic signal model), accelerometer arrays can separate gravity from platform acceleration [203], [334]. However, the required hardware is not and will not be practical for this type of navigation in the near future.

• Uncertainty assessment: Since the same quantities are measured by multiple sensors in the array, the consistency between the measurements can be checked and used for sensor fault detection and isolation, increasing the reliability of the inertial sensor array [26], [317]. Further, the redundant measurements can also be used to estimate the uncertainty of the same, and by introducing a (low parameterized) model for the measurement uncertainties, the measurement fusion algorithm can be designed to adapt to the error characteristics of the sensors [5], [300]. The uncertainty in the estimated linear and angular motion parameters can also be calculated.

#### B. Fundamental requirements and limitations

To be able to achieve the listed capabilities there are certain requirements the array must fulfill, and there are also fundamental limits to what can be achieved with certain types of arrays. These requirements and limitations are:

• *Geometry requirements*: To be able extract 3 degrees-offreedom rotational motion information from the accelerometers in the array, it is necessary that the array holds at

<sup>2</sup>The assumption that  $\sum \mathbf{r}^{(i)} = \mathbf{0}$  implies that the effects of the centrifugal and the Euler force cancel out when averaging the measurements.

<sup>3</sup>Information in the terms of Fisher information.



Fig. 2. Publications per year and the cumulative number of publications in the field of inertial sensor arrays from 1962 to the spring of 2016.

least 6 (single axis) accelerometers whose locations span a 3 dimensional space or or at least 9 (single axis) accelerometers whose locations span a 2 dimensional space [258], [273]. The rotational motion information gained is proportional to the square of the scale of the distance between the accelerometers [273] and, depending on the number of sensors and their geometry, the complexity of calculating the rotational motion information varies (see Sec. III-B for details.).

• *Identifiability and accuracy limitations*: In arrays made out of only accelerometers, the sign of the angular velocity cannot be determined from the measurements taken at a single time instant since the Coriolis force is quadratic in the angular velocity. Further, even if sign of the angular velocity where known, the variance of any unbiased (accelerometer measurement based) estimator of the angular velocity tends to infinity as the angular velocity goes towards zero [273].

#### C. Practical problems

Beyond the fundamental limitations of the inertial sensor arrays, there are several practical problems related to the design and use of the arrays. For reliable rotational motion information to be extractable from accelerometers, their placement within the array must be known with very high degree of precision<sup>4</sup>. Further, the mutual orientation of the sensitivity axes of the sensors must also be well known. Calibration of these parameters along with standard parameters such as sensor biases and scale factor errors are essential to obtain the full capability of an inertial sensor array. Finally, the sampling of the sensors needs to be well (time) synchronized.

#### **III. LITERATURE REVIEW**

There are some +300 publications in the field of inertial sensor arrays, excluding work on fault detection. Inertial sensor arrays, and special cases thereof, go under several different names in the literature, such as gyro-free/non-gyro/all-accelerometer/accelerometer-only/(6-/9-/12-) axis accelerometer IMU/INS, multi-/redundant IMU systems, gyroscope array, accelerometer array. The temporal distribution of the publications can be seen in Fig. 2. Of note is the strong increase in publications around the year 2000 which coincides with the appearance of MEMS-accelerometers on the market. There is

<sup>&</sup>lt;sup>1</sup>To simplify the discussion we will assume that the origin of the array is defined so that  $\sum \mathbf{r}^{(i)} = \mathbf{0}$  and that the triads are independent.

<sup>&</sup>lt;sup>4</sup>To the first order the angular velocity error is proportional to angular speed times the relative position error of the sensor.

a similar trend, not shown in the graph, for an emphasis from around year 2010 on systems based on complete IMUs, which coincides with an increasing availability of complete MEMS-IMUs. In addition to the categorized literature, 10 PhD theses have been published on inertial sensor arrays [3], [17], [37], [53], [88], [127], [212], [215], [238], [325]. Further, 2 old PhD theses have also been cited in the literature [113], [262], but their titles are rather unspecific and we have not been able to verify their content. We also wish to point out some seemingly relavant early work which we have not been able to access [63], [75], [105], [106], [140], [192].

The publications are categorized in Tables I and II based on their objectives and their applications areas, as described in the following subsections. A few publications also deal with attributes of inertial sensor arrays which fall outside the listed categories [14], [32], [42], [62], [294].

#### A. Objectives

The objectives of the publications in the literature are categorized as follows:

• *Measurement fusion*: Publications dealing with how to process and combine the inertial measurements (and possible other information) to attain estimates of s,  $\omega$  and  $\dot{\omega}$  or higher level information such as attitude or position.

• *Calibration and error analysis*: Publications dealing with how to model, estimate and compensate for array imperfections and how errors affect the system.

Sensor constellation optimization: Publications dealing with the constellation geometry and number of sensors to be used.
Experimental platforms: Publications including experimental platforms and evaluations of inertial sensor arrays.

#### B. Array types

The array types in the literature are categorized as follows: • *Accelerometers-only* arrays, with subcategories:

- $\leq 8 \text{ axis}$ : The minimum number of accelerometers needed to extract 3 degrees-of-freedom rotational information is 6. However, with 9 unknowns (s,  $\omega$  and  $\dot{\omega}$ ) and less than 9 measurements, one has to exploit the temporal dependence between  $\omega$  and  $\dot{\omega}$  to attain estimates for the same [309]. This creates an additional integration for the inertial mechanization, increasing the error growth rate [191], [232]. The 6 sensor configuration requires a non-coplanar array geometry.
- 9–11 axis: With 9 or more accelerometers it is possible to estimate s,  $\omega$  (with sign ambiguity) and  $\dot{\omega}$  directly. This eliminates the hard dependence on the extra integration, except for resolving the sign of  $\omega$ . The 9 sensor configuration enables the use of a coplanar array geometry.
- $\geq 12$  axis: With 12 or more accelerometers, a linear relaxation can be introduced, enabling a least-squares framework to be used for estimating s,  $\omega$  (with sign ambiguity) and  $\dot{\omega}$ . This is convenient, but requires a non-coplanar array and gives a suboptimal performance [273]. Not all methods dealing with 12 or more accelerometers

exploit this relaxation, see e.g. [39], [43], [273], but for simplicity they are all classified in the same category.

• Accelerometers and gyroscopes: In arrays made out of both accelerometers and gyroscopes the number and the configuration of accelerometers is of less significance. The sign ambiguity of  $\omega$  disappears but the challenge is in how to combine the angular motion information from the accelerometers and the gyroscopes measurements.

The listed categories make up the vast majority of the presented systems. However, there also exist publications on several other array setups. Gyroscopes only arrays, which only have the capability to quantify and mitigate the effect of the measurement errors [19], [20], [22], [45], [46], [71], [104], [119], [154], [181], [189], [265], [314], [315], [323]. Arrays made out of *identical accelerometers* (and gyroscopes) integrated on a chip level, in which case the distances between the accelerometers are negligible and one may only quantify and mitigate the effect of the measurement errors [25], [163], [199], [330]. Arrays constructed out of accelerometers with different dynamic range, but with insignificant spatial separation. This enables an increased specific force dynamic measurement range and measurement accuracy, but no other capabilities [24], [143], [200], [256]. Distributed (semi-rigid) inertial networks [9], [157], [162]. There also exist publications on dynamic accelerometer and other more complex inertial sensors [11], [44], [47], [66], [67], [74], [95], [100], [145], [168], [197], [205], [207], [219], [279].

#### C. Application areas

The actual/suggested applications are classified as follows: • *Biomechanics*: This is the most common application area for accelerometer-only arrays, which are especially used for crash and impact tests for vehicle safety and sport medicine. In these fields, short highly dynamic motions and forces resulting in linear and angular accelerations are studied, which is suitably done with accelerometer arrays. For a general review on so called accelerometry, see [110].

• *Navigation*: This is the most common application for combined accelerometer and gyroscope arrays. Previously, general navigation with arrays of only accelerometers has been suggested, often motivated by the high cost of gyroscopes. But due to the poor performance of accelerometer-only arrays at low angular velocities and the availability of low-cost gyroscopes, these type of systems are today only motivated in certain niche-applications.

• *Ballistic platform guidance*: This may be viewed as navigation with very special requirements. Munition is often subject to very high acceleration making usage of gyroscopes difficult. However, the motion is highly dynamic, short and constrained, facilitating the usage of accelerometer-only systems.

• *Platform control*: Platform control and especially stabilization benefits from the capability to directly estimate angular acceleration. This enables acceleration mode control, which can significantly increase the servo bandwidth, as compared to angular velocity mode control. • Other: Application areas such as gravity gradiometry, vibration sensing, and gesture detection.

#### **IV. KEY REFERENCES**

The field exhibits a large degree of redundancy, also in the publications. Many results have been reproduced over and over again. However, the key results and a good overview of the field can be attained from a small number of key references which we would like to point out:

• A. Schuler et al. (1967) [263], an early account of the theory for handling 6 and 9 axis accelerometer-only arrays.

• A. Padgaonkar et al. (1975) [231], an account of the theory and experimental data for a 9 axis accelerometer-only array. • J. Angeles et al. (1987) [13], contains the first account of the linear relaxation enabling a least squares solution for s,  $\omega$ and  $\dot{\omega}$  for a general (non-coplanar) accelerometers array.

• P. Cardou et al. (2008) [39], an account of methods to solve the nonlinear estimation for an accelerometer-only array.

• M. Pachter et al. (2013) [230], inertial navigation, mechanization, and error analysis of accelerometer-only arrays.

• I. Skog et al. (2016) [273], estimation-theoretical formulation of inertial arrays containing accelerometers and gyroscopes.

#### V. OUTLOOK

Motion sensing is a fundamental property and inertial sensor cost, size, power consumption, and performance are steadily improving. Inertial sensors are already present in large numbers, in everything from gadgets to industrial systems, and will be present in even larger numbers in more and more systems. Already today, inertial sensors are packaged with microcontrollers; high-end tactical and navigation grade sensors are reaching price levels where new applications are within reach; and novel high-end technologies such as atom interferometry-based accelerometers are emerging. This will create numerous opportunities for applying inertial sensor array techniques. However, still lacking are solid and mature methods such as:

- Combined adaptive statistical tools for estimation, faultdetection, and uncertainty assessment.
- Robust automatic online array calibration tools including time synchronization of different inertial signals.
- Methods for combining asynchronous inertial sensors with different dynamic range, bandwidth, error/stability characteristics and sampling frequency.

These are among the current and future challenges for researchers involved in the field of inertial sensor arrays and a prerequisite for capitalizing upon the new opportunities that comes with new inertial sensor hardware and systems.

#### REFERENCES

- [1] E. Akeila, Z. Salcic et al., "Implementation, calibration and testing of GFINS models based on six-accelerometer cube," in TENCON, Nov. 2008
- [2] Y. Al-Rawashdeh, M. Elshafei et al., "In-flight estimation of center of gravity position using all-accelerometers," Sensors, vol. 14, no. 9, 2014.
- [3] M. Algrain, "On the optimal estimation of 3-D angular motion," Ph.D. dissertation, Illinois Institute of Technology, 1991.

- "Gyroless platform stabilization techniques," US Patent [4] -5 124 938, 1992.
- [5] "Accelerometer-based platform stabilization," in Proc. SPIE 1482, Acquisition, Tracking, and Pointing V, 1991.
- [6] M. Algrain and J. Quinn, "Accelerometer based line-of-sight stabilization approach for pointing and tracking systems," in Proc. IEEE Conf. on Control Applicat., Sep. 1993.
- [7] M. Algrain and J. Saniie, "Estimation of 3D angular motion using gyroscopes and linear accelerometers," IEEE Trans. Aerosp., vol. 27, no. 6, pp. 910-920, 1991.
- [8] D. Allerton and H. Jia, "Redundant multi-mode filter for a navigation system," IEEE Trans. Aerosp. Electron. Syst., vol. 43, no. 1, pp. 371-391, 2007.
- [9] "Distributed data fusion algorithms for inertial network systems," IET Radar Sonar Navig., vol. 2, no. 1, pp. 51-62, 2008.
- "An error compensation method for skewed redundant inertial [10] configuration," in Proc. 58th Annu. Meeting of ION and CIGTF 21st Guidance Test Symp., Jun. 2002.
- [11] R. Amarasinghe, D. V. Dao et al., "Development of miniaturized 6-axis accelerometer utilizing piezoresistive sensing elements," Sensors and Actuat. A-Phys., vol. 134, pp. 310-320, 2007.
- [12] W.-T. Ang, P. Khosla et al., "Design of all-accelerometer inertial measurement unit for tremor sensing in hand-held microsurgical instrument," in Proc. ICRA, vol. 2, Sep. 2003.
- [13] J. Angeles, "Computing of rigid-body-angular acceleration from pointacceleration measurements," J. Dyn. Sys., Meas., Control, vol. 109, pp. 124-127, 1987.
- [14] -, "The angular-acceleration tensor of rigid-body kinematics and its properties," *Archive of Appl. Mech.*, vol. 69, pp. 204–214, 1999. [15] J. Bancroft, "Multiple IMU integration for vehicular navigation," in
- Proc. ION GNSS, Sep. 2009.
- [16] J. Bancroft and G. Lachapelle, "Data fusion algorithms for multiple inertial measurement units," Sensors, vol. 12, pp. 3720-3738, 2011.
- [17] J. Bancroft, "Multiple inertial measurement unit integration for pedestrian navigation," Ph.D. dissertation, University of Calgary, 2010.
- [18] V. Baraniello and F. Corraro, "Unconventional integrated navigation systems based on redundancy of traditional navigation sensors," in Proc. AIAA Guidance, Navigation, and Control Conf., Aug. 2010.
- [19] D. Bayard, "Combining multiple gyroscope outputs for increased accuracy," NASA Tech Briefs, pp. 36-37, Jun. 2003.
- [20] D. Bayard and S. Ploen, "High accuracy inertial sensors from inexpensive components," US Patent 006 882 964B2, 2005.
- [21] J. Beckwith, J. Chu et al., "Validation of a noninvasive system for measuring head acceleration use during boxing competition," J Appli Biomech, vol. 23, pp. 238-244, 2007.
- [22] A. Bejczy, "Non-orthogonal redundant configurations of single-axis strap-down gyros," JPL Quarterly Technical Review, vol. 1, no. 2, 1971. [23] F. Bendjellal, X. Trosseille *et al.*, "Measurement of head angular
- acceleration with a 15 accelerometer array," in Proc. 16th Annu. Int. Workshop on Human Subjects for Biomechanical Research, Oct. 1988.
- [24] P. Björkholm, L. Landén et al., "Navigation in vehicle crash test using MEMS-based IMU," in *Proc. PLANS*, May 2010. R. Boysel and J. Sampsell, "Micro-machined accelerometer array with
- [25] shield plane," US Patent 5 551 293, 1996.
- [26] S. Brás, P. Rosa et al., "Fault detection and isolation in inertial measurement units based on bounding sets," IEEE Trans. Automat Contr, vol. 60, no. 7, pp. 1933-1938, 2015.
- [27] I. Brooks, "Spatially distributed measurements of platform motion for the correction of ship-based turbulent fluxes," Journal of Atmospheric and Oceanic Technology, vol. 25, pp. 2007–2017, 2008. T. Brunner, S. Changey *et al.*, "Multiple MEMS-IMU localization:
- [28] Architecture comparison and performance assessment," in ICINS, 2015.
- [29] A. Buhmann, C. Peters et al., "A GPS aided full linear accelerometer based gyroscope-free navigation system," in Proc. PLANS, Apr. 2006.
- [30] W. Bussone, R. Bove et al., "Six-degree-of-freedom accelerations: Linear arrays compared with angular rate sensors," SAE Tech. Paper, 2010.
- [31] D. Camarillo, P. Shull et al., "An instrumented mouthguard for measuring linear and angular head impact kinematics in american football," Annals of Biomedical Eng., vol. 41, no. 9, pp. 1939–1949, 2013.
- Y. Cao and J. Zu, "Review of the gyroscope free strap-down inertial navigation system," in *Proc. ICCASM*, 2010. [32]
- [33] P. Cappa, F. Patané et al., "Two calibration procedures for a gyroscopefree inertial measurement system based on a double-pendulum apparatus," Meas. Sci. and Tech., vol. 19, no. 5, p. 055204, 2008.
- [34] P. Cappa, L. Masia et al., "Numerical validation of linear accelerometer systems for the measurement of head kinematics," J. Biomech. Eng., vol. 127, no. 6, pp. 919-928, 2005.

# TABLE I Publication sorted by array type and content. Papers may be listed at multiple entries if covering multiple objectives. References are numbered and listed in alphabetical order.

	Array type			
Content	Accelerometers only		Accelerometers & gyroscopes	
Measurement fusion	$\leq 8$ axis	9-11 axis	$\geq 12$ axis	
		[2], [4], [5], [6], [18], [34], [36], [38], [51], [56], [64], [65], [76], [78], [79], [80], [81], [96], [103], [132], [133], [141], [142], [144], [155], [156], [159], [164],	[2], [7], [13], [29], [34], [35], [38], [39], [36], [40], [41], [43], [50], [57], [61], [64], [65], [70], [85], [86], [87], [92], [111], [112], [126], [136], [138], [139],	[15], [16], [18], [28], [30], [48], [60], [68], [89], [90], [91], [98], [99], [107], [108], [109], [114], [116], [117], [118], [120], [121], [122], [123], [125], [148], [159], [160], [170],
	[228], [231], [234], [236], [263], [277], [280], [282], [285], [283], [284], [302], [304], [311], [320], [324]	[172], [173], [176], [180], [182], [183], [190], [201], [206], [213], [218], [223], [224], [231], [237], [250], [251], [258], [263], [266], [269], [281], [296], [297], [298], [299], [303], [311], [331], [332]	[158], [166], [171], [172], [173], [187], [188], [194], [196], [202], [220], [230], [235], [239], [241], [242], [243], [246], [252], [259], [260], [261], [289], [291], [311], [313], [319], [328], [333], [334]	[184], [185], [186], [198], [200], [204], [221], [226], [233], [247], [253], [271], [278], [286], [291], [293], [300], [305], [308], [312], [316], [322], [326], [327]
Calibration and error analysis	[1], [33], [70], [77], [82], [126], [131], [141], [142], [146], [147], [165], [196], [217], [222],       [8], [10], [27], [54], [55], [72],         [228], [237], [239], [240], [242], [248], [257], [259], [261], [267], [284], [285], [296], [306],       [137], [149], [167], [249], [329]         [324]       [324]       [324]       [324]			
Optimization of sen- sor constellation	[52], [101], [129], [130], [139], [175], [188], [196], [211], [252], [260], [258], [285], [307], [125], [134], [150], [151], [309], [310], [318], [328] [125], [244], [245], [253], [268], [274], [276]			
Experimental platform	[1], [5], [6], [29], [31], [33], [138], [139], [146], [156], [15 [209], [213], [214], [217], [21 [264], [277], [282], [292], [30	[35], [43], [52], [56], [73], [76], 8], [164], [166], [169], [174], [1 8], [223], [227], [228], [231], [2 2], [319], [321], [295]	, [77], [80], [82], [102], [111], 75], [194], [196], [201], [202], 43], [246], [251], [258], [261],	[15], [16], [48], [55], [59], [61], [90], [91], [98], [99], [107], [108], [109], [114], [115], [120], [124], [160], [176], [186], [198], [200], [204], [221], [226], [229], [233], [242], [270], [272], [278], [286], [288], [291], [301], [300]

#### TABLE II

PUBLICATION SORTED BY ARRAY TYPE AND INTENDED APPLICATION AREA. PAPERS NOT STATING AN EXPLICIT APPLICATION AREA ARE NOT LISTED. REFERENCES ARE NUMBERED AND LISTED IN ALPHABETICAL ORDER.

	Array type		
Application area	Accelerometers only	Accelerometers & gyroscopes	
Biomechanical/crash tests	[21], [23], [31], [34], [35], [56], [69], [83], [97], [102],	[24], [30], [159], [160], [226], [301]	
	[103], [111], [128], [135], [136], [141], [156], [158],		
	[159], [196], [202], [213], [214], [223], [231], [255],		
	[264], [275], [281], [295], [321]		
Navigation	[29], [38], [70], [79], [81], [87], [92], [178], [180], [183],	[15], [16], [59], [68], [107], [108], [109], [124], [134],	
	[220], [230], [236], [246], [251], [280], [285], [289],	[198], [221], [229], [253], [254], [271], [276], [278],	
	[308], [331]	[286], [287], [327]	
Ballistic platform guidance	[58], [64], [65], [66], [101], [112], [132], [133], [176],	[193], [312]	
	[195], [208], [225], [234]		
Platform stabilization and control	[5], [6], [4], [174], [177]	[98], [99], [291], [290]	
Other	[2], [12], [33], [73], [74], [93], [94], [96], [153], [161],	[115], [185]	
	[201], [209], [216], [227], [277], [298], [304], [320],		
	[333], [334]		

- [35] P. Cappa, F. Patanè *et al.*, "A redundant accelerometric cluster for the measurement of translational and angular acceleration and angular velocity of the head," *J. Med. Devices*, vol. 1, no. 1, pp. 14–22, 2007.
- [36] P. Cardou, "Computing the rigid-body acceleration field from nine accelerometer measurements," in *Brain, Body and Machine*, ser. Advances in Intelligent and Soft Computing, J. Angeles, B. Boulet *et al.*, Eds. Springer Berlin Heidelberg, 2010, vol. 83, pp. 325–339.
- [37] —, "Design of multiaxial accelerometers with simplicial architectures for rigid-body pose-and-twist estimation," Ph.D. dissertation, McGill University, 2008.
- [38] P. Cardou and J. Angeles, "A comparative study of all-accelerometer strapdowns for UAV INS," in *Proc. RTO-MP-SET-092*, 2005.
- [39] —, "Angular velocity estimation from the angular acceleration matrix," J. Appl. Mech., vol. 75, 2008.
- [40] —, Angular-Velocity Estimation from the Centripetal Component of the Rigid-Body Acceleration Field. Springer, 2008, pp. 353–360.

- [41] —, "Estimating the angular velocity of a rigid body moving in the plane from tangential and centripetal acceleration measurements," *Multibody Syst. Dynamics*, vol. 19, pp. 383–406, 2008.
- [42] —, "Linear estimation of the rigid-body acceleration field from point-acceleration measurements," J. Dynamic Sys., Meas., and Cont., vol. 131, 2009.
- [43] P. Cardou, G. Fournier *et al.*, "A nonlinear program for angular-velocity estimation from centripetal-acceleration measurements," *IEEE/ASME Trans. Mechatronics*, vol. 16, no. 5, pp. 932–944, 2011.
- [44] H. Chan, H. J. Paik *et al.*, "Superconducting techniques for gravity survey and inertial navigation," *IEEE Trans. Magn.*, vol. 21, no. 2, pp. 411–414, 1985.
- [45] H. Chang, L. Xue *et al.*, "Combining numerous uncorrelated MEMS gyroscopes for accuracy improvement based on an optimal Kalman filter," *IEEE Trans. Instrum. Meas.*, vol. 61, no. 11, pp. 3084–3093, 2012.

- [46] —, "An integrated MEMS gyroscope array with higher accuracy output," Sensors, vol. 8, no. 4, p. 2886, 2008.
- [47] V. Chapsky, V. T. Portman *et al.*, "Single-mass 6-DOF isotropic accelerometer with segmented PSD sensors," *Sensors and Actuat. A-Phys.*, vol. 135, pp. 558–569, 2007.
- [48] G. Chatterjee, L. Latorre *et al.*, "Smart-MEMS based inertial measurement units: gyro-free approach to improve the grade," *Microsystem Technologies*, pp. 1–10, Dec. 2015.
- [49] J.-H. Chen, S.-C. Lee *et al.*, "Gyroscope free strapdown inertial measurement unit by six linear accelerometers," *J. Guid. Control. Dynam.*, vol. 17, no. 2, pp. 286–290, 1994.
- [50] T.-L. Chen, "Design and analysis of a fault-tolerant coplanar gyro-free inertial measurement unit," J. Microelectromechanical Syst., vol. 17, no. 1, pp. 201–212, Feb. 2008.
- [51] T.-L. Chen and S. Park, "MEMS SoC: observer-based coplanar gyrofree inertial measurement unit," J. Micromechanics and Microengineering, vol. 15, no. 9, p. 1664, 2005.
- [52] J. Cheng, J. Dong *et al.*, "A novel optimal configuration form redundant MEMS inertial sensors based on the orthogonal rotation method," *Sensors*, vol. 14, pp. 13661–13678, 2014.
- [53] T. Chien, "An adaptive technique for a redundant-sensor navigation system," Ph.D. dissertation, Massachusetts Institute of technology, 1972.
- [54] S. Cho and C. Park, "Calibration of a redundant IMU," in Proc. AIAA Guidance, Navigation, and Control Conf. and Exhibit, Aug. 2004.
- [55] —, "A calibration technique for a redundant IMU containing lowgrade inertial sensors," *ETRI J.*, vol. 27, no. 4, pp. 418–426, 2005.
- [56] C. Chou and S. Sinha, "On the kinematics of the head using linear acceleration measurements," *J. Biomechanics*, vol. 9, no. 10, pp. 607 – 613, 1976.
- [57] N. Ciblak, "Determining the angular motion of a rigid body using linear accelerometers without integration," in *Proc. RAST*, Jun. 2007.
- [58] G. Clark, "Angular and linear velocity estimation for re-entry vehicle using six distributed accelerometers: Theory, simulation, and feasibility," Lawrence Livemore Nat. Lab., Tech. Rep., 2003.
- [59] P. Clausen, J. Skaloud *et al.*, "Position accuracy with redundant MEMS IMU for road applications," *European J. of Navigation*, vol. 13, pp. 4– 12, 2015.
- [60] I. Colomina, M. Giménez et al., "On the use of redundant inertial data for geodetic applications," in Proc. ION GNSS, 2004.
- [61] I. Colomina, M. Gimnez et al., "Redundant IMUs for precise trajectory determination," in Proc. ISPRS Congr., Jul. 2004.
- [62] D. Condurache, M. Matcovschi *et al.*, "Computation of angular velocity and acceleration tensors by direct measurements," *Acta Mechanica*, vol. 153, pp. 147–167, 2002.
- [63] V. Corey, "Measuring angular acceleration with linear accelerometers," *Control Engineering*, Mar. 1962.
- [64] M. Costello, "Determining the angular velocity and angular acceleration of a projectile using triaxial acceleration measurements," in *Proc. AIAA Atmospheric Flight Mechanics Conf.*, 2000.
- [65] M. Costello and T. Jitpraphai, "Determining angular velocity and angular acceleration of projectiles using triaxial acceleration measurements," *J Spacecr Rockets*, vol. 39, no. 1, pp. 73–80, 2002.
- [66] M. Costello and C. Webb, "Angular rate estimation using an array of fixed and vibrating triaxial acceleration measurements," in *Proc. AIAA Atmospheric Flight Mech. Conf. and Exhibit*, Aug. 2003.
- [67] —, "Angular rate estimation using fixed and vibrating triaxial acceleration measurements," J. Spacecraft, vol. 42, pp. 1133–1137, 2005.
- [68] T. Crain, R. Bishop et al., "Shifting the inertial navigation paradigm with MEMS technology," in Proc. AAS 33rd Annual Guidance and Control Conf., Feb. 2010.
- [69] J. Crisco and R. Greenwald, "System and method for measuring the linear and rotational acceleration of a body part," US Patent 008 554 509B2, 2013.
- [70] D. Cucci, O. Crespillo et al., "An analysis of a gyro-free inertial system for INS/GNSS navigation," in ENC, 30 Jun. - 2 May 2016.
- [71] X. Dai, L. Zhao *et al.*, "Optimal sensor fusion in redundant inertial measurement unit," *Applied Mechanics and Materials*, vol. 433-435, pp. 250–253, 2013.
- [72] E. J. de Oliveira, W. de Castro Leite Filho *et al.*, "Inertial measurement unit calibration procedure for a redundant tetrahedral gyro configuration with wavelet denoising," *J. Aerosp. Technol. Manag.*, vol. 4, no. 2, pp. 163–168, 2012.
- [73] F. Di Puccio and P. Forte, "Identification of the 3D vibratory motion of a rigid body by accelerometer measurements," *Shock and Vibrations*, vol. 11, pp. 281–293, 2004.

- [74] D. Dichev, H. Koev et al., "A gyro-free system for measuring the parameters of moving objects," *MEASUREMENT SCIENCE REVIEW*, vol. 14, no. 5, pp. 263–269, 2014.
- [75] L. DiNapoli, "Measurement of angular velocities without the use of gyros," Master's thesis, Univ. of Pennsylvania, 1965.
- [76] M. Ding, Q. Wang et al., "A novel non-gyro inertial measurement unit," Key Engineering Materials, vol. 295-296, pp. 583–588, 2005.
- [77] M. Ding, T. Liang *et al.*, "Design and study of error compensation method for improving the precision of angular rates of nongyro inertial measurement units," *J. of Micro/Nanolithography, MEMS, and MOEMS*, vol. 9, no. 3, 2010.
- [78] M. Ding and Q. Wang, "An integrated navigation system of NGIMU/GPS using a fuzzy logic adaptive Kalman filter," in *Proc. FSKD*, 2005.
- [79] —, Proc. Int. Cobn. Fuzzy Systems and Knowledge Discovery. Springer, 2005, ch. An Integrated Navigation System of NGIMU/ GPS Using a Fuzzy Logic Adaptive Kalman Filter, pp. 812–821.
- [80] M. Ding, W. Wei et al., "Design of a nine-accelerometer non-gyro inertial measurement unit," in Proc. SPIE 5634, Advanced Sensor Syst. and Applicat. II, vol. 5634, 2005, pp. 739–747.
- [81] M. Ding, Q. Zhou et al., "Application of a static and dynamic united decoupling method for non-gyro inertial measurement unit," in Proc. SPIE 6571, Multisensor, Multisource Inform. Fusion: Architectures, Algorithms, and Applicat., vol. 6571, 2007.
- [82] D. Dube and P. Cardou, "The calibration of an array of accelerometers," *Trans. CSME*, vol. 35, no. 2, pp. 251–267, 2011.
- [83] S. Duma, S. Manoogian *et al.*, "Analysis of real-time head accelerations in collegiate football players," *Clin J Sport Med*, vol. 15, pp. 3–8, 2005.
- [84] A. Edmund, F. Marques *et al.*, "Integrated GPS/INS navigation system based on a gyroscope-free IMU," in *Proc. DINCON*, 2006.
- [85] E. Edwan, S. Knedlik *et al.*, "Constrained angular motion estimation in a gyro-free IMU," *IEEE Trans. Aerosp. Electron. Syst.*, vol. 47, no. 1, pp. 596–610, Jan. 2011.
- [86] —, "Angular motion estimation using dynamic models in a gyro-free inertial measurement unit," *Sensors*, vol. 12, pp. 5310–5327, 2012.
- [87] —, "GPS/INS integration for GF-IMU of twelve mono-axial accelerometers configurations," in *Proc. WPNC*, Mar. 2009.
- [88] E. Edwan, "Novel approaches for improved performance of inertial sensors and integrated navigation systems," Ph.D. dissertation, Universitt Siegen, 2013.
- [89] T. Ell and R. Rutkiewicz, "High bandwidth inertial measurement unit," US Patent 008 020 442B2, 2011.
- [90] F. Evans and J. Wilcox, "Experimental strapdown redundant sensor inertial navigation system," in AIAA Guidance, Control and Flight Mechanics Conference, Aug. 1969.
- [91] —, "Experimental strapdown redundant sensor inertial navigation system," J. Spacecr, vol. 7, no. 9, pp. 1070–1074, 1970.
- [92] Q. Fang-Jun, X. Jiang-ning *et al.*, "A novel attitude algorithm for 12 accelerometer based gfins using hermite interpolation," in *Proc. ICMTMA*, vol. 1, Mar. 2010, pp. 214–217.
- [93] B. Favre-Bulle, Robot Motion Trajectory-Measurement with Linear Inertial Sensors. InTech, 2005, ch. 8.
- [94] M. Fehringer, G. Andre *et al.*, "A jewel in esa's crown," *ESA bullentin*, vol. 133, pp. 14–23, 2008.
- [95] S. Fengjia and F. Shangchun, "Angular acceleration calculation method on non-gyro inertial measurement unit," in *Sixth Intl. Symp. on Instrumentation and Control Technology*, 2006.
- [96] P. Frere, "Problems of using accelerometers to measure angular rate in automobiles," *Sensors and Actuators, A: Physical*, vol. 25-27, pp. 821–824, 1991.
- [97] K. Fyfe, J. Rooney *et al.*, "Motion analysis system," US Patent 006 513 381B2, 2003.
- [98] M. Gajamohan, M. Merz et al., "The cubli: A cube that can jump up and balance," in *IEEE/RSJ International Conference on Intelligent Robots and Systems*, Oct. 2012.
- [99] M. Gajamohan, M. Muehlebach *et al.*, "The cubli: A reaction wheel based 3D inverted pendulum," in *ECC*, Jul. 2013.
- [100] Z. Gao and D. Zhang, "Design, analysis and fabrication of a multidimensional acceleration sensor based on fully decoupled compliant parallel mechanism," *Sensors and Actuat. A-Phys.*, vol. 163, pp. 418– 427, 2010.
- [101] J. Genin, J. Hong et al., "Accelerometer placement for angular velocity determination," J. Dyn. Sys., Meas., Control, vol. 119, pp. 474–477, 1997.
- [102] D. Giansanti and G. Maccioni, "Comparison of three different kinematic sensor assemblies for locomotion study," *Physiological Meas.*, vol. 26, pp. 689–705, 2005.

- [103] D. Giansanti, V. Macellari et al., "Is it feasible to reconstruct body segment 3-D position and orientation using accelerometric data?" IEEE Trans. Biomed. Eng., vol. 50, no. 4, pp. 476-483, 2003.
- [104] J. Gilmore, "Conceptual nonorthogonal gyro configuration for guidance and navigation," NASA Tech Briefs, no. 19670000433, Nov 1967.
- -, "A non-orthogonal gyro configuration," Master's thesis, Mas-[105] sachusetts Institute of Technology, 1967.
- [106] "A non-orthogonal multi-sensor strapdown inertial reference unit," in EASCON, Sep. 1968.
- J. Gilmore and R. Cooper, "SIRU development final report volume I [107] system development," Massachusetts Inst. of Tech., Tech. Rep., 1973.
- [108] J. Gilmore and R. McKern, "A redundant strapdown inertial reference unit (SIRU)," J Spacecr Rockets, vol. 9, no. 1, pp. 39-47, 1972.
- [109] R. Giroux, S. Sukkarieh et al., "Implementation of a skewed-redundant low-cost INS in a fast prototyping environment," in Proc. ION NTM, Jan. 2004.
- [110] A. Godfrey, R. Conway et al., "Direct measurement of human move-ment by accelerometry," *Medical Engineering & Physics*, vol. 30, no. 10, p. 13641386, 2008.
- [111] J. Gong and J. Lach, "Reconfigurable differential accelerometer platform for inertial body sensor networks," in IEEE SENSORS, Nov. 2013.
- [112] P. Goulart, "A dynamics based method for accelerometer-only navigation of a spinning projectile," Master's thesis, Massachusetts Institute of Technology, 2001.
- A. Grammatikos, "Gimballess inertial systems for space navigation," [113] Ph.D. dissertation, University of Pennsylvania, 1965.
- [114] D. Greenheck, "Design and characterization of a low cost MEMS IMU cluster for precision navigation," Master's thesis, Marquette University, 2015
- [115] D. Greenheck, R. Bishop et al., "Design and testing of a low-cost MEMS IMU cluster for smallsat applications," in Proc. AIAA/USU Conf. on Small Satellites, 2014.
- [116] L. Grigorie and R. Botez, "Modeling and numerical simulations of an algorithm for the inertial sensors errors reduction and for the increase of the strap-down navigation redundancy degree in a low cost architecture," Trans. of the CSME, vol. 34, no. 1, pp. 1-16, 2010.
- -, "Miniaturised inertial sensors noise reduction by using redundant [117] linear configurations," in Proc. IASTED ASM, Jun. 2011.
- [118] -, "A new method to reduce the noise of the miniaturised inertial sensors disposed in redundant linear configurations," The Aeronautical J., vol. 117, no. 1188, pp. 111-132, 2013.
- -, "Precision improvement of aircrafts attitude estimation through [119] gyro sensors data fusion in a redundant inertial measurement unit," in IPSN, Apr. 2014.
- [120] T. Grigorie, R. Botez et al., "Experimental testing of a data fusion algorithm for miniaturized inertial sensors in redundant configurations," in Proc. MMSSE, Feb. 2014.
- [121] T. Grigorie, I. Edu et al., "Fuzzy logic denoising of the miniaturized inertial sensors in redundant configurations," in Proc. ITI, Jun. 2011, pp. 521–526.
- [122] T. Grigorie, R. Botez et al., "Navigation solution errors reduction through inertial sensors data fusion in a redundant bi-dimensional strapdown inertial navigator," in Proc. EngOpt, Jul. 2012.
- [123] , "A redundant bi-dimensional inertial navigator in vertical plane," in Proc. International conference on circuits, 2012.
- [124] Y. Gu, Q. Song et al., "An anchor-based pedestrian navigation approach using only inertial sensors," *Sensors*, vol. 16, no. 3, p. 334, 2016. [125] S. Guerrier, "Improving accuracy with multiple sensors: Study of
- redundant MEMS-IMU/GPS configurations," in Proc. ION GNSS, Sep. 2009
- [126] P. Gullipalli and K. Ariyur, "Accelerometer based IMUs," in ITM, Jan. 2011.
- [127] L. Haibo, "Key technique of micro inertial system based on redundant gyroscopes," Ph.D. dissertation, Harbin Engineering University, 2011.
- [128] E. Hanlon and C. Bir, "Validation of a wireless head acceleration measurement system for use in soccer," J. Appli. Biomech., vol. 26, pp. 424-431, 2010.
- [129] R. Hanson, "Using multiple MEMS IMUs to form a distributed inertial measurement unit," Master's thesis, Air University, 2005.
- [130] R. Hanson and M. Pachter, "Optimal gyro-free IMU geometry," in Proc. AIAA Guidance, Navigation, and Control Conf., Aug. 2005.
- [131] Y. Hao and Z. Liu, "Analysis and calibration on installation errors of accelerometer in GFSINS," in Proc. CCDC, 2009.
- [132] T. Harkins, "Assessing the feasibility of accelerometer-only inertial measurements units for artillery projectiles," Army Research Laboratory, Tech. Rep., 1994.
- T. Harkins and T. Brown, "Practicability issues in deriving angular rates [133] from accelerometer data for the 2.75-inch MK66 rocket," in Proc. 18th Int. Symp. on Ballistics, Nov. 1999.

- [134] J. Harrison and E. Gai, "Evaluating sensor orientations for navigation performance and failure detection," IEEE Trans. Aerosp. Electron. Syst., vol. AES-13, no. 6, pp. 631-643, Nov. 1977.
- [135] V. Hasija, E. Takhounts et al., "Finding 3D angular accelerations of a rigid body from in-plane accelerometers using optimization," in Proc. Injury Biomechanics Research, 2004.
- [136] W. Hayes, J. Gran et al., "Leg motion analysis during gait by multiaxial accelerometry: Theoretical foundations and preliminary validations.' ASME. J Biomech Eng., vol. 105, no. 3, pp. 283-289, 1983.
- [137] K. He, J. Han et al., "A novel redundant inertial measurement unit and calibration algorithm," in *ICOM*, Sept. 2013.
- [138] P. He and P. Cardou, "Estimating the angular velocity from bodyfixed accelerometers," J. Dyn. Sys., Meas., Control, vol. 134, no. 6, p. 061015, 2012.
- [139] C.-W. Ho and P.-C. Lin, "Design and implementation of a 12-axis accelerometer suite," in Proc. IROS, Oct. 2009, pp. 2197–2202.
- [140] A. Hu, "Rotational measurement techniques using linear accelerometers," in Proc. Int. Instrumentation Symp., May 1977.
- [141] "Angular acceleration measurement errors induced by linear accelerometer cross-axis coupling," The Shock and Vibration Bulletin, vol. 50, no. 2, pp. 11-16, 1980.
- [142] A. Hu and A. Johnson, "Cross-axis eeffect on the measurement of angular acceleration using linear accelerometers," in *Proc. of the Int.* Workshop on Human Subject's for Biomechanical Research, 1976.
- [143] T. Hudson, S. Holt *et al.*, "Multi-sensor inertial array technologies for advanced microsystems," in *Proc. PLANS*, Apr. 2006, pp. 574–585.
- [144] R. Huijser, "Assembly of accelerometers for use in a system for measuring the three dimensional movements of a rigid body," Europe Patent 0 556 487A1, 1993.
- [145] R. Hulsing, "Single coriolis inertial rate and acceleration sensor," Navigation, vol. 35, no. 3, 1988.
- C.-Y. Hung, C.-M. Fang et al., "A compensator to advance gyro-free INS precision," Int. J. of Control, Automation, and Syst., vol. 4, no. 3, [146] pp. 351-358, 2006.
- [147] C.-Y. Hung and S.-C. Lee, "A calibration method for six-accelerometer INS," Int. J. of Control, Automation, and Syst., vol. 4, no. 5, pp. 615-623, 2006.
- [148] M. Jafari, T. Najafabadi et al., "PEM stochastic modeling for MEMS inertial sensors in conventional and redundant IMUs," IEEE Sensors J., vol. 14, no. 6, pp. 2019–2027, Jun. 2014.
- [149] M. Jafari, M. Sahebjameyan et al., "Skew redundant MEMS IMU calibration using a Kalman filter," Meas. Sci. and Technol., vol. 26, p. 105002, 2015.
- [150] M. Jafari and J. Roshanian, "Inertial navigation accuracy increasing using redundant sensors," J. Sci. and Eng., vol. 1, no. 1, pp. 55-56, 2013.
- [151] , "Optimal redundant sensor configuration for accuracy and reliability increasing in space inertial navigation systems," J. of Navigation, vol. 66, no. 2, pp. 199-208, Mar. 2013.
- [152] M. Jafari, "Optimal redundant sensor configuration for accuracy increasing in space inertial navigation system," Aerospace Sci. and Tech., vol. 47, pp. 467-472, Dec. 2015.
- [153] S. Jeon and M. Tomizuka, "Benefits of acceleration measurement in velocity estimation and motion control," Control Engineering Practice, vol. 15, pp. 325-332, 2007.
- [154] C. Jiang, L. Xue et al., "Signal processing of MEMS gyroscope arrays to improve accuracy using a 1st order Markov for rate signal modeling,' Sensors, vol. 12, no. 2, pp. 1720-1737, 2012.
- [155] Y. Jintao, "A novel design of NGIMU," in *GRS*, Dec. 2008.
  [156] B. Juhas, J. Wong *et al.*, "Semi-rigid helmet rotation measurement using linear accelerometers," in *Proc. ASME Int. Mechanical Eng.* Congr. and Exposition, Nov. 2013.
- J. Kaiser, G. Beck et al., "Vital advanced inertial network," in IEEE [157] PLANS, Apr. 1998.
- [158] T. Kane, W. Hayes et al., "Experimental determination of forces exerted in tennis play," Biomechanics IV, pp. 284-290, 1974.
- Y. Kang, K. Moorhouse et al., "Measurement of six degrees of freedom [159] head kinematics in impact conditions employing six accelerometers and three angular rate sensors (6a $\omega$  configuration)," ASME. J Biomech Eng., vol. 133, no. 11, Dec. 2011.
- [160] "Instrumentation technique for measuring six degrees of freedom head kinematics in impact conditions using six-accelerometers and three-angular rate sensors ( $6a\omega$  configuration) on a lightweight tetrahedron fixture," in Proc. 24th Enhanced Safety of Vehicles (ESV) Conference, Jun. 2015.
- [161] C. Kao and T. Chen, "Design and analysis of an orientation estimation system using coplanar gyro-free inertial measurement unit and magnetic sensors," Sensors Actuat. A-Phys., vol. 144, no. 2, pp. 251 - 262, 2008.

- [162] R. Kelley, N. Carlson *et al.*, "Integrated inertial network," in *IEEE PLANS*, Apr. 1994.
- [163] S. Kim and K. Chun, "A new inertial sensing paradigm using an accelerometer array: XL-array," in *Conf. on Device and Process Technologies for MEMS and Microelectronics*, Oct. 1999.
- [164] A. King, A. Padgaonkar et al., "Measurement of angular acceleration of a rigid body using linear accelerometers," in Proc. of the Int. Workshop on Human Subject's for Biomechanical Research, 1974.
- [165] I. Klein, "Analytic error assessment of gyro-free ins," J. Appl. Geodesy, vol. 9, no. 1, pp. 49–61, 2015.
- [166] B. Koçer, V. Ömürlü *et al.*, "Development of a MEMs-based IMU unit," in *RAST*, Jun. 2013.
- [167] A. Kozlov, I. Sazonov *et al.*, "IMU calibration on a low grade turntable: Embedded estimation of the instrument displacement from the axis of rotation," in *Proc. ISISS*, Feb. 2014.
- [168] V. Krishnan, "Measurement of angular velocity and linear acceleration using linear accelerometers," *J. of the Franklin Institute*, vol. 280, no. 4, p. 307315, 1965.
- [169] T. Kröer, D. Kubus *et al.*, "12d force and acceleration sensing: A helpful experience report on sensor characteristics," in *Proc. ICRA*, May 2008.
- [170] D. Kulmaczewski, "Inertial measurement unit providing linear and angular outputs using only fixed linear accelerometer sensors," US Patent 005 383 363A, 1995.
- [171] V. Larin and A. Tunik, "Algorithms of gyro-free accelerometer-based satellite-inertial navigation system," *J Electronics and Control Systems*, vol. 4, no. 34, 2012.
- [172] —, "Gyro-free accelerometer-based sins: Algorithms and structures," in *Proc. MSNMC*, 2012.
- [173] —, "On inertial-navigation system without angular-rate sensors," Int. Appl. Mechanics, vol. 49, no. 4, pp. 488–499, 2013.
- [174] W. Latt, U.-X. Tan *et al.*, "Placement of accelerometers for high sensing resolution in micromanipulation," *Sensors Actuat. A-Phys.*, vol. 167, no. 2, pp. 304 – 316, 2011, solid-State Sensors, Actuators and Microsystems Workshop.
- [175] —, "Compact sensing design of a handheld active tremor compensation instrument," *IEEE Sensors J.*, vol. 9, no. 12, pp. 1864–1871, Dec. 2009.
- [176] F. Lawrence, B. Mills *et al.*, "Extending the impulse measurement capability at the arnold engineering development center to six degrees of freedom," in *Proc. AIAA Aerodynamic Measurement Technology and Ground Testing Conf.*, Jun. 2002.
- [177] S. Lee, G. Ortiz *et al.*, "Increasing tracking bandwidth for deep-space optical communications using linear accelerometers," IPN Progress Report, Tech. Rep., 2003.
- [178] S.-C. Lee and Y.-C. Huang, "Innovative estimation method with measurement likelihood for all-accelerometer type inertial navigation system," *IEEE Trans. Aerosp. Electron. Syst.*, vol. 38, no. 1, pp. 339– 346, Jan. 2002.
- [179] S.-C. Lee and C.-Y. LiU, "An innovative estimation method with ownship estimator for an all-accelerometer-type inertial navigation system," *Int. J. of Syst. Sci.*, vol. 30, no. 12, pp. 1259–1266, 1999.
- [180] S. Lei, H. Chang-Qiang *et al.*, "Research on a new eight-accelerometer configuration for attitude angle calculation of uav," in *Proc. CCDC*, May 2010.
- [181] M. Leszczynski, "Improving the performance of MEMS gyros via redundant measurements: Theory and experiments," Master's thesis, Naval Postgraduate School, 2014.
- [182] A. Li, F. Qin et al., "Gyroscope free strapdown inertial navigation system using rotation modulation," in Proc. ICICTA, Oct. 2009.
- [183] X. Li, Y.-Q. Zhang *et al.*, "Study of a self-adaptive Kalman filter method in NGMIMU/GPS integrated navigation scheme," in *Proc. Int. Asia Conf. on Ind. Eng. and Manage. Innovation*, Oct. 2015.
- [184] P.-C. Lin and C.-W. Ho, "Design and implementation of a 9-axis inertial measurement unit," in *Proc. ICRA*, May 2009.
- [185] P.-C. Lin, H. Komsuoğlu *et al.*, "Sensor data fusion for body state estimation in a hexapod robot with dynamical gaits," *IEEE Trans. Robot.*, vol. 22, no. 5, pp. 932–943, 2006.
- [186] P.-C. Lin, J.-C. Lu et al., "Design and implementation of a nine-axis inertial measurement unit," *IEEE/ASME Trans. Mechatronics*, vol. 17, no. 4, pp. 657–668, 2012.
- [187] C. Liu, S. Yu *et al.*, "An effective unscented Kalman filter for state estimation of a gyro-free inertial measurement unit," in *Proc. PLANS*, May 2014.
- [188] C. Liu, S. Zhang *et al.*, "Design and analysis of gyro-free inertial measurement units with different configurations," *Sensors Actuat. A-Phys.*, vol. 214, pp. 175–186, Aug. 2014.

- [189] J. Liu, Q. Shen *et al.*, "Signal processing technique for combining numerous MEMS gyroscopes based on dynamic conditional correlation," *Micromachines*, vol. 6, no. 6, pp. 684–698, Jun. 2015.
- [190] T. Liu, G. rong Zhao et al., "An intelligent weighted method of calculating angular-velocity in GFSINS," in Proc. ICIEA, May 2009, pp. 1805–1808.
- [191] Y. Liu, "Discussion: measurement of angular acceleration of a rigid body using linear accelerometers," *J. of Appl. Mechanics*, vol. 43, no. 2, pp. 377–378, 1976.
- [192] V. Lopatin, Measurement of angular velocity of aircraft by means of linear accelerometers. Washington, DC: Joint Publication Research Service, Mar. 1967.
- [193] A. Lovas, K. Massey et al., "DARPA SCORPION Program Transition to Army Lethality ATO Program: A Success Story," in Proc. Joint Armaments Conf., Exhibition & Firing Demonstration, 2010.
- [194] J.-C. Lu and P.-C. Lin, "State derivation of a 12-axis gyroscope-free inertial measurement unit," *Sensors*, vol. 11, no. 3, pp. 3145–3162, 2011.
- [195] D. Lyon, "Advanced technologies for embedded instrumentation," in Int. Armaments Technology Symp. & Exhibition, 2004.
- [196] S. Madgwick, A. Harrison *et al.*, "Measuring motion with kinematically redundant accelerometer arrays: Theory, simulation and implementation," *Mechatronics*, vol. 23, no. 5, pp. 518–529, 2013.
- [197] T. Mairson, "Apparatus and method for performing inertial measurements using translational acceleration transducers and for calibrat'ing translational acceleration transducers," US Patent 4 188 816, 1980.
- [198] P. Marinushkin and I. Podshivalov, "MEMS-based non-orthogonal redundant inertial measurement unit for miniature navigation systems," in *SIBCON*, May 2015.
- [199] E. Markert, M. Dienel et al., "Modeling of a new 2d acceleration sensor array using SystemC-AMS," in Proc. Int. MEMS Conf., 2006.
- [200] H. Martin, P. Groves et al., "A new approach to better low-cost MEMS IMU performance using sensor arrays," in Proc. ION GNSS+, Sep. 2013.
- [201] P. Martin, G. Hall *et al.*, "Measuring the acceleration of a rigid body," *Shock and Vibrations*, vol. 5, pp. 211–224, 1998.
- [202] K. Matsumura and T. Yamamoto, "A wearable accelerometer array for human movement analysis based on rbsn approach," SICE J. of Control, Meas., and Syst. Integration, vol. 4, no. 3, pp. 206–213, May 2011.
- [203] J. McGuirk, G. Foster et al., "Sensitive absolute-gravity gradiometry using atom interferometry," Phys. Rev. A, vol. 65, Feb 2002.
- [204] R. McKern and J. Gilmore, "A redundant strapdown inertial system mechanization - SIRU," in AIAA Guidance, Control and Flight Mechanics Conference, Aug. 1970.
- [205] S. Merhav, "Apparatus and method for measuring specific force and angular rate," US Patent 4 445 376, 1984.
- [206] —, "Signal processor for inertial measurement using coriolis force sensing accelerometer arrangements," US Patent 4 870 588, 1989.
- [207] —, "A nongyroscopic inertial measurement unit," J. Guidance, vol. 5, no. 3, pp. 227–235, 1982.
- [208] W. Mickelson, "Navigation system for spinning projectile," US Patent 006 163 021A, 2000.
- [209] M. Miles, "Measurement of six-degree of freedom model motions using strapdown accelerometers," in *Proc. 21st American Towing Tank Conf.*, Aug. 1986.
- [210] N. Mimura, "Method for measuring 6 degrees of freedom motion and device therefor," US Patent 006 128 955A, 2000.
- [211] D. Mingli, Z. Qingdong *et al.*, "Feasibility analysis of accelerometer configuration of non-gyro micro inertial measurement unit," in *Proc. IPEMC*, vol. 3, Aug. 2006.
- [212] N. Mital, "Computation of rigid body rotation in three-dimensional space from body-fixed acceleration measurements," Ph.D. dissertation, Wayne State University, 1978.
- [213] N. Mital and A. King, "Computation of rigid-body rotation in threedimensional space from body-fixed linear acceleration measurements," *J. Appl. Mech.*, vol. 46, pp. 925–930, 1979.
- [214] J. Morris, "Accelerometrya technique for the measurement of human body movements," J. Biomechanics, vol. 6, no. 6, p. 729732, 1973.
- [215] K. Mostov, "Design of accelerometer-based gyro-free navigation system," Ph.D. dissertation, U.C. Berkeley, 2000.
- [216] K. Mostov, A. Soloviev *et al.*, "Accelerometer based gyro-free multisensor generic inertial device for automotive applications," in *Proc. ITSC*, Nov. 1997, pp. 1047–1052.
- [217] —, "Accelerometer-based gyro-free multi-sensor INS," in Annual Meeting of The Institute of Navigation, Jun. 1998.
- [218] M. Nabih and G. Holstein, "Measurement of 3-D motion," in Proc. Int. Workshop on Human Subjects for Biomedical Research., Oct. 1977.

- [219] S. Nakamura, "Mems inertial sensor toward higher accuracy & multiaxis sensing," in IEEE Sensors, Irvine, CA, USA, 30 Oct. - 3 Nov. 2005.
- [220] H. Naseri and M. Homaeinezhad, "Improving measurement quality of a MEMS-based gyro-free inertial navigation system," Sensors Actuat. A-Phys., vol. 207, pp. 10–19, Mar. 2014.
- [221] J.-O. Nilsson, A. K. Gupta et al., "Foot-mounted inertial navigation made easy," in IPIN, Oct. 2014.
- [222] J.-O. Nilsson, I. Skog et al., "Aligning the forces eliminating the misalignments in IMU arrays," IEEE Trans. Instrum. Meas., vol. 63, no. 10, pp. 2498-2500, Oct. 2014.
- [223] G. Nusholtz, "Geometric methods in determining rigid-body dynam-Experimental Mechanics, vol. 33, no. 2, pp. 153-158, 1993
- [224] G. Nusholtz and J. Wu, "Direct measurement of angular velocity using the 3-2-2-2 linear accelerometer configuration," in Proc. 19th Annual Workshop on Human Subjects for Biomechanical Research, 1991.
- [225] E. Ohlmeyer and T. Pepitone, "Guidance, navigation and control without gyros: a gun-launched munition concept," in Proc. AIAA Guidance, Navigation, and Control Conf. and Exhibit, Aug. 2002.
- [226] N. Okita and H. Sommer, "Angular acceleration of the foot during gait using an IMU," in Annual conference of the American Society of Biomechanics, 2013.
- R. Onodera and N. Mimura, "Stability and error analysis of a new 6 [227] DOF motion sensor using multiple accelerometers," in Proc. Sensors, Oct. 2007, pp. 752-755.
- -, 6-DOF Motion Sensor System Using Multiple Linear Accelerom-[228] eters. InTech, 2009, ch. 13.
- A. Osman, B. Wright *et al.*, "Multi-sensor inertial navigation systems [229] employing skewed redundant inertial sensors," in Proc. ION GNSS, Sept. 2006.
- [230] M. Pachter, T. C. Welker et al., "Gyro-free ins theory," Navigation, vol. 60, p. 8596, 2013.
- [231] A. Padgaonkar, K. W. Krieger et al., "Measurement of angular acceleration of a rigid body using linear acceleration," J. Appl. Mech., vol. 42, pp. 552-556, 1975
- [232] -, "Closure to discussion of measurement of angular acceleration of a rigid body using linear accelerometers," J. Appl. Mech., vol. 43, no. 2, p. 378, 1976.
- [233] A. Pahadia, "GPS/INS integration aided with gyroscope-free IMU for pedestrian applications," Master's thesis, University of Calgary, 2010.
- [234] K. Pamadi, E. Ohlmeyer et al., "Assessment of a GPS guided spinning projectile using an accelerometer-only IMU," in Proc. AIAA Guidance, Navigation, and Control Conf. and Exhibit, 2004.
- [235] S. Park and S. K. Hong, "Angular rate estimation using a distributed set of accelerometers," *Sensors*, vol. 11, no. 11, pp. 10444–10457, 2011. [236] S. Park and C.-W. Tan, "GPS-aided gyroscope-free inertial navigation
- systems," University of California Berkeley, Tech. Rep., 2002.
- [237] S. Park, C.-W. Tan et al., "A scheme for improving the performance of a gyroscope-free inertial measurement unit," Sensors Actuat. A-Phys., vol. 121, no. 2, pp. 410 - 420, 2005.
- [238] K. Parsa, "Dynamics, state estimation, and control of manipulators with rigid and flexible subsystems," Ph.D. dissertation, McGill University, 2003
- [239] K. Parsa, J. Angeles et al., "Pose-and-twist estimation of a rigid body using accelerometers," in Proc. ICRA, vol. 3, 2001, pp. 2873-2878
- [240] "Attitude calibration of an accelerometer array," in Proc. ICRA, vol. 1, 2002, pp. 129-134.
- "Rigid-body pose and twist estimation using an accelerometer [241] array," Archive of Appl. Mechanics, vol. 74, no. 3-4, pp. 223-236, 2004.
- [242] K. Parsa, T. Lasky et al., "Design and mechatronic implementation of an accelerometer-based, kinematically redundant inertial measurement unit," in Proc. IEEE/ASME AIM, Jul. 2005, pp. 644-651.
- [243] "Design and implementation of a mechatronic, all-accelerometer inertial measurement unit," IEEE/ASME Trans. Mechatronics, vol. 12, no. 6, pp. 640-650, Dec. 2007.
- [244] A. Pejsa, "ptimum orientation and accuracy of redundant sensor arrays," in AIAA 9th Aerospace Sciences Meeting, Jan. 1971. —, "Optimum skewed redundant inertial navigators," AIAA J.,
- [245] vol. 12, no. 7, pp. 899-902, 1974.
- [246] Y. Peng and M. Golnaraghi, "A vector-based gyro-free inertial navigation system by integrating existing accelerometer network in a passenger vehicle," in *Proc. PLANS*, Apr. 2004, pp. 234–242.
- [247] J.-P. Petillon, "Method and system for estimating the angular speed of a mobile," US Patent 2010/0268414 A1, 2010.
- [248] M. Pittelkau, "Calibration and attitude determination with redundant inertial measurement units," J. Guid. Control. Dynam., vol. 28, no. 4, pp. 743–752, 2005.
- -, "Cascaded decoupled RIMU calibration filters," The J. of the [249] Astronautical Sciences, vol. 54, no. 3, pp. 449-466, 2006.

- [250] F. Qin, J. Xu et al., "A new scheme of gyroscope free inertial navigation system using 9 accelerometers," in Proc. ISA, 2009.
- [251] L. Qin, W. Zhang et al., "Attitude measurement system based on microsilicon accelerometer array," Chaos, Solitons & Fractals, vol. 29, no. 1, pp. 141 - 147, 2006.
- [252] Z. Qin, L. Baron et al., "Robust design of inertial measurement units based on accelerometers," J. Dyn. Sys., Meas., Control, vol. 131, no. 3, p. 031010, 2009.
- [253] M. Rhudy, J. Gross et al., "Fusion of GPS and redundant IMU data for attitude estimation," in Proc. AIAA Guidance, Navigation, and Control Conf., Aug. 2012.
- [254] F. Riewe, "Low-cost multiple sensor inertial measurement system for locomotive navigation," Transport Research Board National Reseach Council, Tech. Rep., 2000.
- [255] S. Rowson, J. Beckwith et al., "A six degree of freedom head acceleration measurement device for use in football," J. Appl. Biomechanics, vol. 27, pp. 8-14, 2011.
- [256] P. Ruffin, "MEMS-based sensor arrays for military applications," in Proc. SPIE Smart Structures and Materials 2002, 2002
- P. Schopp, H. Graf et al., "Self-calibration of accelerometer arrays," [257] IEEE Trans. Instrum. Meas., 2016, accepted for publication.
- "Observing relative motion with three accelerometer triads," [258] IEEE Trans. Instrum. Meas., vol. 63, no. 12, pp. 3137-3151, Dec. 2014.
- P. Schopp, L. Klingbeil et al., "Sensor fusion algorithm and calibration [259] for a gyroscope-free IMU," in Proc. Eurosensors XXIII Conf., 2009.
- P. Schopp, A. Rottmann et al., "Gaussian process based state estimation [260] for a gyroscope-free IMU," in Proc. Sensors, Nov. 2010, pp. 873-878.
- [261] P. Schopp, L. Klingbeil et al., "Design, geometry evaluation, and calibration of a gyroscope-free inertial measurement unit," Sensors and Actuat. A-Phys., vol. 162, no. 2, pp. 379 - 387, Aug. 2010.
- A. Schuler, "Design and analysis of analytic platform inertial naviga-[262] tion systems," Ph.D. dissertation, University of Pennsylvania, 1965.
- A. Schuler, A. Grammatikos et al., "Measuring rotational motion with [263] linear accelerometers," IEEE Trans. Aerosp. Electron. Syst., vol. AES-3, no. 3, pp. 465-472, May 1967.
- [264] R. Shea and D. Viano, "Computing body segment trajectories in the hybrid iii dummy using linear accelerometer data," J. Biomech. Eng., vol. 116, pp. 37-43, 1994.
- [265] Q. Shen, W. Yuan et al., "A virtual gyroscope based-on a single-chip four-microgyroscope array," in Proc. NEMS, Apr. 2014.
- [266] Z. Shi, J. Yang et al., "Angular velocity estimation in gyroscope-free inertial measurement system based on unscented Kalman filter," in Proc. World Congress on Intelligent Control and Automation, 2010.
- [267] -, "A new calibration and compensation method for installation errors of accelerometers in gyroscope free strap-down inertial navigation system," in Proc. International Conference on Information and Automation, 2010.
- [268] D.-S. Shim and C.-K. Yang, "Optimal configuration of redundant inertial sensors for navigation and fdi performance," Sensors, vol. 10, no. 7, pp. 6497-6512, 2010.
- [269] M. Shu-zhi, B. Xiong-zhu et al., "Optimization design and calibration of installation error coefficients for gyroscope-free strapdown inertial measurement unit," in Proc. ICMA, Jun. 2006.
- [270] I. Skog, J.-O. Nilsson et al., "An open-source multi inertial measure-ment unit (MIMU) platform," in Proc. ISISS, Feb. 2014.
- -, "Pedestrian tracking using an IMU array," in Proc. CONECCT, [271] Jan. 2014.
- -, "Arrays of single-chip IMUs," in Proc. IPIN, 2015. [272]
- [273] -, "Inertial Sensor Arrays, Maximum Likelihood, and Cramér-Rao Bound," IEEE Trans. Signal Process., 2016, accepted for publication.
- [274] J. Song and C. Park, "Optimal configuration of redundant inertial sensors considering lever arm effect," IEEE Sensors J., vol. PP, no. 99, pp. 1-1, 2015.
- [275] R. Stirling, J. Collin et al., "An innovative shoe-mounted pedestrian navigation system," in GNSS, Apr. 2003.
- [276] M. Sturza, "Skewed axis inertial sensor geometry for optimal performance," in Proc. 8th AIAA/IEEE Digital Avionics Syst. Conf., Oct. 1988, pp. 128-135.
- [277] V. Subramanian and C. Vendhan, "An efficient algorithm for strapdown accelerometer-based motion measurement," Ocean Eng., vol. 20, no. 4, pp. 421-432, 1993
- [278] S. Sukkarieh, P. Gibbens et al., "A low-cost, redundant inertial measurement unit for unmanned air vehicles," Int. J. Robot. Res., vol. 19, pp. 1089-1103, 2000.
- [279] G. Sun and Q. Gu, "Accelerometer based north finding system," in Proc. PLANS, 2000.

- [280] P. Sungsu and T. Chin-Woo, "GPS-aided gyroscope-free inertial navigation systems," California Partners for Advanced Transit and Highways (PATH), Tech. Rep., 2002.
- [281] E. Takhounts, R. Eppinger et al., "Analysis of 3D rigid body motion using the nine accelerometer array system," in Injury Biomechanics Research: Proc. of the Thirty-First Int. Workshop, 2003.
- [282] C.-W. Tan, K. Mostov et al., "Feasibility of a gyroscope-free inertial navigation system for tracking rigid body motion," California PATH Research Report, Tech. Rep. UCB-ITS-PRR-2000-9, 2000.
- [283] C.-W. Tan and S. Park, "Design and error analysis of accelerometerbased inertial navigation systems," California PATH Research Report, Tech. Rep. UCB-ITS-PRR-2002-21, 2002.
- [284] "Design of accelerometer-based inertial navigation systems,"
- IEEE Trans. Instrum. Meas., vol. 54, no. 6, pp. 2520-2530, Dec. 2005. C.-W. Tan, S. Park *et al.*, "Design of gyroscope-free navigation systems," in *Proc. ITSC*, Aug. 2001. [285]
- M. Tanenhaus, D. Carhoun et al., "Miniature IMU/INS with optimally [286] fused low drift MEMS gyro and accelerometers for application in GPSdenied environments," in Proc. PLANS, Apr. 2012.
- [287] M. Tanenhaus, T. Geis et al., "Accurate real time inertial navigation device by application and processing of arrays of MEMS inertial sensors," in Proc. PLANS, May 2010, pp. 20-26.
- [288] M. Tanenhaus, D. Carhoun et al., "Precision navigation for UAVs, mini-munitions, and handhelds through application of low cost accurate MEMS IMU/INS technology," in *Proc. PLANS*, May 2008. [289] P. Thompson, "Rotational rate estimation using multiple accelerome-
- ters," in AIAA Atmospheric Flight Mechanics Conference, 2000
- [290] S. Trimpe, "Distributed and event-based state estimation and control," Ph.D. dissertation, Hamburg University of Technology, 2013.
- [291] S. Trimpe and R. DAndrea, "Accelerometer-based tilt estimation of a rigid body with only rotational degrees of freedom," in IEEE ICRA, May 2010. [292] Y.-L. Tsai, T.-T. Tu et al., "EcoIMU: A compact, wireless, gyro-free
- inertial measurement unit based on two triaxial accelerometers," in Proc. IPSN, Apr. 2011.
- [293] D. Tzidon and A. Braginsky, "Sensor cluster navigation device and method," US Patent 20110209544A1, 2011.
- [294] E. Vaknin and I. Klein, "Feasibility of coarse alignment in gyro-free systems," in ENC, Apr. 2015.
- [295] A. van den Bogert, L. Read et al., "A method for inverse dynamic analysis using accelerometry," J. of Biomechanics, vol. 29, no. 7, pp. 949-954, 1996.
- [296] J. Vreeburg, "Analysis of the data from a distributed set of accelerometers, for reconstruction of set geometry and its rigid body motion," in Proc. AIP Conf., vol. 458, no. 1, Feb. 1999, pp. 496-509.
- [297] -, "Angular rate from the nine accelerometer instrument," J. Appl. Mech., vol. 77, no. 6, p. 061008, 2010.
- [298] "Prony analysis of flat-spin motion from accelerometer data," IEEE Trans. Aerosp. Electron. Syst., vol. 48, no. 2, pp. 1080-1099, 2012.
- [299] J. Vreeburg and R. Huijser, "Assembly of linear accelerometers mounted on a rigid body remote from the center of mass measuring three dimensional movements," US Patent 5408879, 1995.
- [300] A. Waegli, J. Skaloud et al., "Noise reduction and estimation in multiple micro-electro-mechanical inertial systems," Meas. Sci. and Tech., vol. 21, 2010.
- A. Waegli, S. Guerrier et al., "Redundant MEMS-IMU integrated with [301] GPS for performance assessment in sports," in Proc. PLANS, May 2008
- [302] D. Wang and G. Yuan, "A six-degree-of-freedom acceleration sensing method based on six coplanar single-axis accelerometers," IEEE Trans. *Instrum. Meas.*, vol. 60, no. 4, pp. 1433–1442, Apr. 2011. [303] Q. Wang, M. Ding *et al.*, "A new scheme of non-gyro inertial
- measurement unit for estimating angular velocity," in Proc. IECON, vol. 2, Nov. 2003, pp. 1564-1567
- [304] X. Wang and C. Yang, "Constructing gyro-free inertial measurement unit from dual accelerometers for gesture detection," Sensors & Transducers J., vol. 171, no. 5, pp. 134-140, May 2014.
- [305] N. Watson, "Accelerometer system," US Patent 4 601 206, 1986.
  [306] X. Weiguang, D. Mingli *et al.*, "Application of total least square algorithm in static decoupling of NGMIMU," Chinese J. Aeronautics, vol. 17, no. 4, 2004.
- [307] T. Williams and K. Fyfe, "Planar accelerometer configurations," J. Appl. Mech., vol. 71, no. 1, pp. 10–14, 2004.
  [308] T. Williams, A. Pahadia *et al.*, "Using an accelerometer configuration
- to improve the performance of a MEMS IMU: Feasibility study with a pedestrian navigation application," in Proc. ION GNSS, Sep. 2009.
- T. Williams, D. Raboud et al., "Minimal spatial accelerometer config-[309] urations," J. Dyn. Sys., Meas., Control, vol. 135, p. 021016, 2013.

- [310] C.-H. Wu and Y.-C. Tseng, "Deploying sensors for gravity measurement in a body-area inertial sensor network," IEEE Sensors Journal, vol. 13, no. 5, pp. 1522-1533, 2012.
- [311] Q. Wu, Q. Jia et al., "Angular velocity estimation based on adaptive simplified spherical simplex unscented Kalman filter in GFSINS," J. Aerospace Eng., vol. 228, no. 8, pp. 1375-1388, 2014.
- -, "A novel high precision inertial measurement scheme and its [312] optimization method for high-speed rotating ammunition," J. Aerospace Eng., vol. 0, pp. 1-14, 2014.
- [313] J. Xudan, M. Zheng et al., "Research on gyroscope free strapdown inertial navigation system based on 3-axis accelerometer," in Proc. ICEMI. 2007.
- [314] L. Xue, C.-Y. Jiang et al., "A novel Kalman filter for combining outputs of MEMS gyroscope array," Measurement, vol. 45, no. 4, pp. 745 -754, 2012
- [315] L. Xue, L. Wang et al., "Analysis of dynamic performance of a Kalman filter for combining multiple MEMS gyroscopes," Micromachines, vol. 5, no. 4, p. 1034, 2014.
- [316] N. Yadav and C. Bleakley, "Two stage Kalman filtering for position estimation using dual inertial measurement units," in Proc. Sensors, 2011.
- [317] C.-K. Yang and D.-S. Shim, "FDI using multiple parity vectors for redundant inertial sensors," European J. Control, vol. 12, pp. 437-449, 2006.
- [318] "Best sensor configuration and accomodation rule based on navigation performance for INS with seven inertial sensors," Sensors, vol. 9, pp. 8456-8472, 2009.
- [319] Y. Yang and X. Yu, "Development of wireless gyroscope-free inertial measurement unit," in International Conference on Advances in Experimental Structural Engineering, Aug. 2015.
- [320] Z. Yang, Y. Shen et al., "Measurement of six degree-of-freedom ground motion by using eight accelerometers," Earthquake Eng. and Eng. Vibration, vol. 4, no. 2, pp. 229-232, 2005.
- [321] N. Yoganandan, J. Zhang et al., "Lightweight low-profile nineaccelerometer package to obtain head angular accelerations in shortduration impacts," J. Biomechanics, vol. 39, pp. 1347 - 1354, 2006.
- [322] P. Yost, "Combining redundant inertial sensors to create a virtual sensor output," US Patent 008 498 827B2, 2013.
- [323] G. Yuan, W. Yuan et al., "Dynamic performance comparison of two Kalman filters for rate signal direct modeling and differencing modeling for combining a MEMS gyroscope array to improve accuracy," Sensors, vol. 15, no. 11, p. 27590, 2015. X. Yuhui, L. Chenggang *et al.*, "Influences analysis of configurations
- [324] on the performance of parallel type six-axis accelerometers," Trans. *FAMENA*, vol. 37, no. 2, pp. 67–86, 2013. [325] Y. Yuksel, "Design and analysis of inertial navigation systems with
- skew redundant inertial sensors," Ph.D. dissertation, University of Calgary, 2011.
- [326] Y. Yuksel and N. El-Sheimy, "An optimal sensor fusion method for skew redundant inertial measurement units," J. Appl. Geodesy, vol. 5, pp. 99-115, 2011.
- [327] S. Yun Cho, H. Keun Lee et al., "Adaptive redundant inertial measurement unit/global positioning system integration filter structure for fault tolerant navigation," ASME. J. Dyn. Sys., Meas., Control, vol. 136, no. 2, Mar. 2014.
- [328] B. Zappa, G. Legnani et al., "On the number and placement of accelerometers for angular velocity and acceleration determination,' J. Dynamic Syst., Meas., and Control, vol. 123, no. 3, pp. 552-554, Sep. 2001
- [329] J. Zhang, Yongyuan et al., "Technique for in-flight calibrating installation errors in multi-IMU redundancy system," in International Conference on Information Technology and Software Engineering, 2012.
- [330] Q.-J. Zhang, R. Kling et al., "Inertial sensing with spatially distributed sensor array and two dimensional data processing," US Patent 20 120 232 832Al, 2012.
- [331] L. Zhao and Z. Chen, "Improvement of the angular velocity precision of gyro-free SINS using residual error estimation algorithm," in Proc. ISIST, Aug. 2004
- [332] W. Zhaohui, L. Xiaopeng et al., "A novel design of a nineaccelerometer non-gyro inertial measurement system," in Proc. IM-CCC, Sep. 2014, pp. 151–155. A. Zorn, "GPS-aided all-accelerometer inertial navigation," in Proc.
- [333] ION GPS, Sep. 2002.
- -, "A merging of system technologies all-accelerometer inertial [334] navigation and gravity gradiometry," in Proc. PLANS, 2002.